

## **OM-20 QC**

The OM-20 is an electrically operated workshop crimping machine designed to up to crimp 11/4" 4 wire and 11/2" 2 wire. Perfect for batch size hose assemblies it is quick, reliable and easy to use. Available in 1 phase and 3 phase (special voltages on request) and comes with an 8 off die set as standard.

The OM-20 QC features a floor mounted quick change rack for die storage and easy changing of die sets.

- Hose capacity 3/16" to 1 1/4" (4 wire) & 1 1/2" (2 wire)
- Dial adjusted digital position indicator
- Available in 1phz or 3phz

- Twin return strut design
- Quick change system
- 8 off die set as standard

TECHNICAL DATA	
Hose capacity:	3/16" - 1 1/4" (4 wire) (1 1/2" 2 wire)
Swaging ranges:	8mm - 66.5mm
Voltages:	220/240 single phase 50/60hz - 380/440 three phase 50/60hz
Radial swaging force:	1,884 kN
Max opening without dies:	99.7mm
Max cycle time:	4 seconds closing 4 seconds opening
Pump:	Twin speed 4600 psi
Weight:	190 kg



## **OM-20 QC**

The OM-20 is an electrically operated workshop crimping machine designed to crimp 1/4" 4 wire and 1 1/2" 2 wire hose assemblies. Perfect for batch size hose assemblies it is quick, reliable and easy to use. Available in 1 phase and 3 phase (special voltages on request) and comes with an 8 off die set as standard.

The OM-20 also has an optional foot pedal and timing circuit feature as an added extra, allowing for timed release control and hands free operation to speed up hose assembly manufacturing times.



## **DIE SET TABLE** Max Ferrule Diameter (mm) Max Ferrule Diameter (mm) Die Set Range (mm) Length (mm) Die Set Range (mm) Length (mm) 08-20\* 08.0 - 09.9 34.0 - 39.9 70.0 46.0 40.0 20.0 34-20 10-20\* 10.0 - 11.9 40.0 22.0 40-20 40.0 - 45.9 70.0 52.0 12.0 - 13.9 40.0 58.0 12-20\* 24.0 46-20 46.0 - 51.9 75.0 14-20\* 14.0 - 15.9 40.0 26.0 52-20\* 52 - 64.0 75.0 64.0 16-20 16.0 - 18.9 40.0 28.0 19-20 19.0 - 21.9 40.0 31.0 22-20 22.0 - 25.9 50.0 34.0 26-20 26.0 - 27.9 50.0 38.0 28-20\* 28.0 - 29.9 50.0 40.0 30.0 - 33.9 60.0 30-20 42.0

\*Non standard dies